

**Celadon Inc.**

**RCV-5000 IR to RS-232 Output Table**

**Device: Panasonic Plasma Display Monitor**

**(may also work with Toshiba and Yamaha Display Monitor)**

Infrared Remote Control: Philips PRONTO, Niles Intellicontrol

Infrared Code Format: NEC - Device ID: 7B02

Infrared Pronto Data File(s): See "IR Code Read Me - RCV-5000.txt" for complete description

Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver

RCV-5000 Data File: panaso1\_r.hex

Data: 9600 Baud, 8, N, 1, ASCII/HEX Output

Switch Pins 2&3

NEEDS GENDER CHANGER

Panasonic Function	Pronto Button	RCV-5000 Output
Power ON	0-00	(02H)PON(03H)
Power OFF	1-01	(02H)POF(03H)
Volume Increase	2-02	(02H)AUU(03H)
Volume Decrease	3-03	(02H)AUD(03H)
Mute (toggle)	4-04	(02H)AMT(03H)
Input Select - AV Mode	5-05	(02H)IIS:VID(03H)
Input Select - Component/RGB Mode (processed as a Y/PB/PR or RGB signal as set by this unit)	6-06	(02H)IIS:YP1(03H)
Input Select - PC Mode	7-07	(02H)IIS:RG1(03H)
Screen Mode Select - Normal (4:3)	8-08	(02H)DAM:NORM(03H)
Screen Mode Select - ZOOM	9-09	(02H)DAM:ZOOM(03H)
Screen Mode Select - FULL	10-0A	(02H)DAM:FULL(03H)
Screen Mode Select - JUST	11-0B	(02H)DAM:JUST(03H)
Screen Mode Select - Panasonic AUTO	12-0C	(02H)DAM:SELF(03H)

Celadon, Inc.

50 Mitchell Blvd.

San Rafael, CA 94903

Sales: (707) 648-1098

Main Tel: (415) 472-1177

Main Fax: (415) 472-1179

sales@celadon.com