

Celadon Inc.

RCV-5000 IR to RS-232 Output Table

**Device: Panasonic TH-42PHD6UY Plasma Display Monitor
(may also work with Toshiba and Yamaha Display Monitor)**

Infrared Remote Control: Philips PRONTO, Niles Intellicontrol

Infrared Code Format: NEC - Device ID: 7B02

Infrared Pronto Data File(s): See "IR Code Read Me - RCV-5000.txt" for complete description

Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver

RCV-5000 Data File: panaso2_r.hex

Data: 9600 Baud, 8, N, 1, ASCII/HEX Output

Switch Pins 2&3

NEEDS GENDER CHANGER

| Panasonic Function | Pronto Button | RCV-5000 Output |
|-------------------------------------|---------------|--------------------|
| Power ON | 0 | (02H)PON(03H) |
| Power OFF | 1 | (02H)POF(03H) |
| Mute - OFF | 2 | (02H)AMT:0(03H) |
| Mute - ON | 3 | (02H)AMT:1(03H) |
| Input Select - Slot1 input | 4 | (02H)IMS:SL1(03H) |
| Input Select - Slot2 input | 5 | (02H)IMS:SL2(03H) |
| Input Select - Slot3 input | 6 | (02H)IMS:SL3(03H) |
| Input Select - PC input | 7 | (02H)IMS:PC1(03H) |
| Screen Mode Select - Normal (4:3) | 8 | (02H)DAM:NORM(03H) |
| Screen Mode Select - ZOOM | 9 | (02H)DAM:ZOOM(03H) |
| Screen Mode Select - FULL | 10 | (02H)DAM:FULL(03H) |
| Screen Mode Select - JUST | 11 | (02H)DAM:JUST(03H) |
| Screen Mode Select - Panasonic AUTO | 12 | (02H)DAM:SELF(03H) |

Celadon, Inc.

50 Mitchell Blvd.

San Rafael, CA 94903

Sales: (707) 648-1098

Main Tel: (415) 472-1177

Main Fax: (415) 472-1179

sales@celadon.com